

### 2S4AE 1.5UP series

2W - Single Output - Fixed Input - Isolated & Unregulated Miniature SIP Package



### **DC-DC Converter**

voltage is required in a distributed power supply system.

2 Watt

Operating temperature range: -40°C to +85°C

High power density

Cooling:

Weight:

Dimensions:

Ultra compact SIP package ♠ Isolation voltage: 1.5kVDC

No external component required

International standard pin-out



1) Where the voltage of the input power supply is stable (voltage variation: ±10%Vin);

The 2S4AE 1.5UP series is especially designed for applications where an isolated

- 2) Where isolation between input and output is necessary (isolation voltage ≤1500VDC);
- 3) Where the output voltage regulation and the ripple & noise of the output voltage is not strictly required;
- 4) Typical application: digit circuit condition; normal low-frequency artificial circuit condition; relay drive circuit condition, etc.



<sup>1.6</sup>g Typ. \* Supply voltage must be discontinued at the end of short circuit duration for others series.

Free air convection

11.60x7.55x10.16 mm

Input specifications					
Item	Test condition	Min	Тур	Max	Units
Input Current (full load / no-load)	• 5V input • 12V input • 24V input		506/23 200/15 105/6	-/60 -/50 -/30	mA mA mA
Input reflected ripple current*			15		mA
Input surge voltage (1sec. max.)	<ul><li>5V input</li><li>12V input</li><li>24V input</li></ul>	-0.7 -0.7 -0.7		9 18 30	VDC VDC VDC
Input filter	Filter capacitor				
Hot Plug	Unavailable				

<sup>\*</sup>Reflected ripple current testing method please see DC-DC Converter Application Notes for specific operation.

Isolation specifications					
Item	Test condition	Min	Тур	Max	Units
Isolation voltage	Input-output, with the test time of 1 minute and the leak current lower than 1mA	1500			VDC VDC
Isolation resistance	Input-output, isolation voltage 500VDC	1000			ΜΩ
Isolation capacitance			20		pF

Output specifications					
Item	Test condition	Min	Тур	Max	Units
Output voltage accuracy	See tolerance envelope graph (Fig. 1)				
Line regulation	For Vin change of 1% • 3.3V output • Other output			±1.5 ±1.2	% %
Load regulation	10%-100% load • 3.3V output • Other output		15 10		% %
Ripple & Noise	20MHz Bandwidth		75	150	mVp-p
Temperature drift	100% full load			±0.03	%/°C
Switching frequency	variable		100		KHz

<sup>\*</sup> Ripple and noise are measured by "parallel cable" method, please see DC-DC Converter Application Notes for specific operation;

EMC specifications			
Emissions	CE	CISPR32/EN55032 CLASS B (see Fig. 4 for recommended circuit)	
Emissions	RE	CISPR32/EN55032 CLASS B (see Fig. 4 for recommended circuit)	
Immunity	ESD	IEC/EN61000-4-2 Contact ±8KV perf. Criteria B	

### 2S4AE\_0505S1.5UP

- 2 = 2Watt; S4 = SIP4; AE = Pinning; 05 = 5Vin; 05 = 5Vout;
- S = Single Output; 1 = 1.5kVDC; U = Unregulated Output P = Short Circuit Protection (SCP)

#### Note:


- All specifications measured at TA = 25°C, humidity < 75%, nominal input voltage and rated output load unless otherwise specified.
- See below recommended circuits for more details.
- 3. If the power module such as the definition of the pin does not match with the hand book, please refer to the actual item.


### 2S4AE 1.5UP series

2W - Single Output - Fixed Input - Isolated & Unregulated Miniature SIP Package


Part Number	Input Voltage [V, Range]	Output Voltage [VDC]	Output current [mA, max/min]	Efficiency @ Full Load [%, min./typ.]	Max. Capacitor load [μF]
2S4AE_0505S1.5UP	5 (4.5-5.5)	5	400/40	75/79	220
2S4AE_0509S1.5UP	5 (4.5-5.5)	9	223/23	80/84	220
2S4AE_0512S1.5UP	5 (4.5-5.5)	12	167/17	75/79	220
2S4AE_0515S1.5UP	5 (4.5-5.5)	15	133/13	75/79	220
2S4AE_0524S1.5UP	5 (4.5-5.5)	24	84/9	80/84	220
2S4AE_1203S1.5UP	12 (10.8-13.2)	3.3	400/40	69/73	220
2S4AE_1212S1.5UP	12 (10.8-13.2)	12	167/17	78/83	220
2S4AE_2405S1.5UP	24 (21.6-26.4)	5	400/40	75/79	220
2S4AE_2415S1.5UP	24 (21.6-26.4)	15	133/13	78/82	220

# Typical characteristics











## **Efficiency**






### 2S4AE 1.5UP series

2W - Single Output - Fixed Input - Isolated & Unregulated Miniature SIP Package

### Typical application circuit


If it is required to further reduce input and output ripple, a filter capacitor may be connected to the input and output terminals, see Fig.3. Moreover, choosing a suitable filter capacitor is very important, start-up problems may be caused if the capacitance is too large. Under the condition of safe and reliable operation, the recommended capacitive load values are shown in Table 1.



Recommended capacitive load value table (Table 1)

Vin (VDC)	Cin (μF)	Vo (VDC)	Cout (µF)
5	4.7	3.3/5/9/12	10
12	2.2	15/24	1
24	1		

### **EMC** solution-recommended



Output	voltage	5/12	24
	C1/C2	4.7μF	/50V
Feeterises	CY		1nF/2KVDC
Emissions C3		Refer to the Cout in Fig.3	
		6.8µH	


Note: 1. 24V input series is subject to CY (CY: 1nF/2KV).


2. It is not needed to add the component in the peripheral circuit when parameter with the symbol of  $_{v}$ –".

# Output load requirements

In order to ensure the converter can work reliably with high efficiency, the minimum load should not less than 10% rated load when it is used. If the needed power is indeed small, please parallel a resistor on the output side (The sum of the efficient power and resistor consumption power is not less than 10%).


### Mechanical dimensions





Note: Unit :mm[inch]

Pin section tolerances:  $\pm 0.10[\pm 0.004]$ General tolerances:  $\pm 0.25[\pm 0.010]$ 



	Pin-Out		
Pi	n	Function	
1	l	GND	
2	2	Vin	
3	3	0V	
4	4	+Vo	